

Amati.linea Amplifier

Amati.linea Amplifier is designed to interconnect with Streaming player w/o amplifier. There are 4 zones on the player which you can enable/disable.

ENG - Data sheet

Issue date 26.11.2021



Application

Music integration into BMS, Multi-room, Control of whole music/player library from touch devices

Types of product

DINAMP Amplifier

Standards and norms compliance

EMC: EN61000-6-1
EN61000-6-3
PCT Certificate

Technical data:

Power supply: 7-36V DC Two slots
Power consumption: 1.2W Idle mode

Connectivity: Enable/Disable input 1
Line-In 1
Stereo Out pair 1

Connections: Power supply: Clamp, 1.5mm², up-to 8A
Inputs: Clamp, 1.5mm²
Stereo Output Screw

Power amplifier
Continues output power 2 x 50W
THD+N 0.07%
SNR 102dB
Features Feedback power stage architecture with PSRR;
Protection against short-circuit;
Thermal protection

Enclosure: Material: Polyamide
Color: Gray
Dimensions: 36(W)x91(H)x56(L) mm

Usage temperature: -5C ... +45C
Storage temperature: -25C ... +55C

Weight: 150g
Warranty: 2 years



Caution Security advice

The installation and assembly of electrical equipment may only be performed by skilled electrician. The devices must not be used in any relation with equipment that supports, directly or indirectly, human health or life or with application that can result danger of people, animals or real value

Mounting advice


The devices are supplied in operational status. The cables connections included can be clamped to the housing if required.

Electrical connection

The devices are constructed for the operation of protective low voltage (SELV). Grounding of device is not needed. When switching the power supply on or off, power surges must be avoided.

Terminal connection scheme

Top connections:



Bottom connections:



